



[www.dekomarkerboards.com](http://www.dekomarkerboards.com)  
phone: 844.366.1545  
[support@dekomarkerboards.com](mailto:support@dekomarkerboards.com)

## SECTION 10115 MARKERBOARDS

### PART 1 - GENERAL

#### 1.1 SECTION INCLUDES

- A. Magnetic, optically clear, ghost-free, shatterproof, resinous markerboards.

#### 1.2 SCOPE

- A. Furnish markerboards, manufacturer's installation kits and accessories as necessary.

#### 1.3 SUBMITTALS

- A. Comply with Section 01330 (01 33 00) – Submittal Procedures.
- B. Product Data: Submit manufacturer's product data, including installation instructions.
- C. Samples: Submit manufacturer's sample of markerboards, 8.5 by 11 inches.
- D. Manufacturer's Certification: Submit manufacturer's certification that materials meet specified material attributes, and are suitable for intended application.
- E. Care and Cleaning Instructions: Submit manufacturer's care and cleaning instructions.
- F. Warranty Documentation: Submit manufacturer's standard warranty.

#### 1.4 DELIVERY, STORAGE, AND HANDLING

- A. Delivery and Acceptance Requirements: Deliver materials to site in manufacturer's original, unopened containers and packaging, with labels clearly identifying product name and manufacturer.
- B. Storage and Handling Requirements:
  - 1. Store and handle materials in accordance with manufacturer's instructions.

2. Keep materials in manufacturer's original, unopened containers and packaging until installation.
3. Store materials indoors in a flat, clean and dry area.
4. Protect materials during storage, handling, and installation to prevent damage.

## **PART II PRODUCTS**

### **2.1 MANUFACTURER**

- A. dekō markerboards | [www.dekomarkerboards.com](http://www.dekomarkerboards.com) | phone: 844.366.1545  
email: [support@dekomarkerboards.com](mailto:support@dekomarkerboards.com)
- B. Substitutes:
  1. Substitutes are not acceptable.  
[OR]
  2. Substitutes acceptable provided they meet the requirements herein.

### **2.2 RESINOUS MARKERBOARDS**

- A. Product Attributes
  1. Ghost-free: impervious to staining from dry-erase, wet-erase and permanent markers.
  2. Weight: .94 lbs SF (non-magnetic) [OR] 2.44 lbs SF (magnetic).
  3. Thickness: 5/32" (non-magnetic) [OR] 1/4" (magnetic)
  4. Shatterproof.
  5. Optically clear writing surface.
  6. Permanent opaque color on back.
- B. Sustainability
  1. Red List Chemical Free: contains no added urea formaldehyde (NAUF), volatile organic compounds (VOCs), polyvinyl chlorides (PVC) or any other chemical on the Red List (Living Building Challenge - May 2014)
  2. Post-Consumer Recycled Content: 33.66% (magnetic)
  3. Pre-Consumer Recycled Content: 18.66% (magnetic)
  4. Made in America
- C. Size
  1. MINI (3'3" x 4')
  2. CLASSIC (4' x 4')
  3. EXECUTIVE (5' x 4")
  4. LITE (3'3" x 8')
  5. TRADITIONAL (4' x 8')
  6. JUMBO (5' x 8')
  7. OTHER (Please Specify)
- D. Color
  1. To be selected from manufacturer's standard line.  
[OR]
  2. Custom

- E. Surface
  - 1. Does not absorb inks or stains, eliminates ghosting.
- F. Corner Detail
  - 1. Crown  
[OR]
  - 2. Radiance
- G. Markerboard Edge
  - 1. Manufacturer's (frameless) Brilliance profile.
- H. Style
  - 1. Non-magnetic  
[OR]
  - 2. Magnetic (standard)
- I. Markerboard Orientation
  - 1. Landscape  
[OR]
  - 2. Portrait
- J. Markerboard Setting
  - 1. Permanent
    - a. Provide manufacturer's recommended Direct-Adhesive setting  
[OR]
  - 2. Removable
    - a. Provide manufacturer's proprietary Z-Clip mounting system
  - 3. Provide manufacturer's installation manual.

### **PART III - EXECUTION**

#### **3.1 EXAMINATION**

- A. Examine walls to ensure they are flat, smooth and ready to receive markerboards.
- B. Notify Architect of conditions that would adversely affect installation or subsequent use.
- C. Do not begin installation until unacceptable conditions are corrected.

#### **3.2 INSTALLATION**

- A. Install dekō markerboards in accordance with manufacturer's instructions at locations indicated on the Drawings.
- B. Install markerboards level, plumb, and at the height indicated.
- C. Leave manufacturer's protective peel-coat on markerboard during the installation process. Do not remove until ready to use.
- D. Prior to initial use, remove peel-coat and clean surface thoroughly in

accordance with manufacturer's written guidelines.

### 3.3 CLEANING

- A. Follow manufacturer's written instructions.
- B. Do not use solvents, harsh chemicals, or abrasive cleaners on your deko markerboard surface.

### 3.4 PROTECTION

- A. Protect installed markerboards from damage during construction.

END OF SECTION